


Compact & Short Type Pad (ø1.5 ~ ø16)

S-ZP



- 6 types of thin UT and thin with ribs CT (10, 13, 16) are added
- 3 types of oval type U (2*4, 3.5*7, 4*10) are added
- Applicable for adapter size



How to Order

Compact vacuum pad S-ZP



Pad diameter

③ Pad type☆	② Pad diameter	02	04	06	08	10	13	16	2004	3507	4010
		ø2	ø4	ø6	ø8	ø10	ø13	ø16	2 x 4	3.5 x 7	4 x 10
U	Flat	●	●	●	●	-	-	-	●	●	●
A1	UT	-	-	-	-	●	●	●	-	-	-
	CT	-	-	-	-	●	●	●	-	-	-
A2	B	-	-	●	●	-	-	-	-	-	-
A3	J	-	-	●	-	-	-	-	-	-	-

④ Material*		<input type="checkbox"/>
N	NBR	<input type="checkbox"/>
S	Silicone rubber	<input type="checkbox"/>

*Refer to page 4 for pad material

Dimensions

(mm)

Compact Pad										Material: NBR(N) Silicone rubber(S)																																																																																			
U	UT	CT								B	J																																																																																		
Flat type	Thin type	Thin type with ribs								Bellows	3-Stage Bellows																																																																																		
			<table border="1"> <thead> <tr> <th>model</th> <th>øA</th> <th>øB</th> <th>øC</th> <th>Y</th> <th>Weight</th> </tr> </thead> <tbody> <tr> <td>S-ZP02U</td> <td>2</td> <td>2.6</td> <td>1.2</td> <td>0.8</td> <td rowspan="3">0.4</td> </tr> <tr> <td>S-ZP04U</td> <td>4</td> <td>4.8</td> <td>1.6</td> <td>1</td> </tr> <tr> <td>S-ZP06U</td> <td>6</td> <td>7</td> <td></td> <td>1</td> </tr> <tr> <td>S-ZP08U</td> <td>8</td> <td>9</td> <td></td> <td>1</td> <td rowspan="3">0.5</td> </tr> <tr> <td>S-ZP10UT</td> <td>10</td> <td>11</td> <td></td> <td>1.5</td> </tr> <tr> <td>S-ZP13UT</td> <td>13</td> <td>14</td> <td></td> <td>1.5</td> </tr> <tr> <td>S-ZP16UT</td> <td>16</td> <td>17</td> <td></td> <td>0.8</td> <td>0.4</td> </tr> <tr> <td>S-ZP10CT</td> <td>10</td> <td>11</td> <td></td> <td>1</td> <td>0.5</td> </tr> <tr> <td>S-ZP13CT</td> <td>13</td> <td>14</td> <td></td> <td>1</td> <td>0.6</td> </tr> <tr> <td>S-ZP16CT</td> <td>16</td> <td>17</td> <td></td> <td></td> <td></td> </tr> </tbody> </table>							model	øA	øB	øC	Y	Weight	S-ZP02U	2	2.6	1.2	0.8	0.4	S-ZP04U	4	4.8	1.6	1	S-ZP06U	6	7		1	S-ZP08U	8	9		1	0.5	S-ZP10UT	10	11		1.5	S-ZP13UT	13	14		1.5	S-ZP16UT	16	17		0.8	0.4	S-ZP10CT	10	11		1	0.5	S-ZP13CT	13	14		1	0.6	S-ZP16CT	16	17				<table border="1"> <thead> <tr> <th>model</th> <th>øA</th> <th>øB</th> <th>øC</th> <th>Weight</th> </tr> </thead> <tbody> <tr> <td>S-ZP06B</td> <td>6</td> <td>7</td> <td>9.1</td> <td rowspan="2">0.4</td> </tr> <tr> <td>S-ZP08B</td> <td>8</td> <td>9</td> <td>10.1</td> </tr> </tbody> </table>		model	øA	øB	øC	Weight	S-ZP06B	6	7	9.1	0.4	S-ZP08B	8	9	10.1	<table border="1"> <thead> <tr> <th>model</th> <th>Weight</th> </tr> </thead> <tbody> <tr> <td>S-ZP06J</td> <td></td> </tr> </tbody> </table>		model	Weight	S-ZP06J	
model	øA	øB	øC	Y	Weight																																																																																								
S-ZP02U	2	2.6	1.2	0.8	0.4																																																																																								
S-ZP04U	4	4.8	1.6	1																																																																																									
S-ZP06U	6	7		1																																																																																									
S-ZP08U	8	9		1	0.5																																																																																								
S-ZP10UT	10	11		1.5																																																																																									
S-ZP13UT	13	14		1.5																																																																																									
S-ZP16UT	16	17		0.8	0.4																																																																																								
S-ZP10CT	10	11		1	0.5																																																																																								
S-ZP13CT	13	14		1	0.6																																																																																								
S-ZP16CT	16	17																																																																																											
model	øA	øB	øC	Weight																																																																																									
S-ZP06B	6	7	9.1	0.4																																																																																									
S-ZP08B	8	9	10.1																																																																																										
model	Weight																																																																																												
S-ZP06J																																																																																													

How to order

Short type vacuum pad S-ZP



- 3 types of Flat type UA (1.5, 2, 3.5) are added
- 6 types of Groove type with ribs UM (4, 10, 16) are added
- 6 types of Bellows BA (4-16) are added

③ Pad type☆	② Pad diameter	B			C			D		
		ø1.5	ø2	ø3.5	ø4	ø6	ø8	ø10	ø13	ø16
UA	Flat type	●	●	●	-	-	-	-	-	-
UM	Groove type with ribs	-	-	-	●	●	●	●	●	●
BA	Bellows	-	-	-	●	●	●	●	●	●

④ Material*		<input type="checkbox"/>
N	NBR	<input type="checkbox"/>
S	Silicone rubber	<input type="checkbox"/>

*Refer to page 4 for pad material

Dimensions

(mm)

Short type pad □ Material: NBR(N) Silicone rubber(S)

UA Flat $\phi 1.5, \phi 2, \phi 3.5$				UM Groove with ribs $\phi 4, \phi 6, \phi 8$					UM Groove with ribs $\phi 10, \phi 13, \phi 16$					
B1				C1					D1					
Part no.	ϕA	ϕB	Weight	Part no.	ϕA	ϕB	ϕC	Y	Weight	Part no.	ϕA	ϕB	Y	Weight
S-ZP015UA □	1.5	2	0.1	S-ZP04UM □	4	4.5	1.2	0.5	0.3	S-ZP10UM □	10	11	1	0.6
S-ZP02UA □	2	2.5		S-ZP06UM □	6	6.5	2	0.8		S-ZP13UM □	13	14	1.2	0.7
S-ZP035UA □	3.5	4		S-ZP08UM □	8	8.5				S-ZP16UM □	16	17		0.8
BA Bellows $\phi 4, \phi 6, \phi 8$				BA Bellows $\phi 10, \phi 13, \phi 16$										
C2				D2										
Part no.	ϕA	ϕB	ϕC	ϕD	Y	Weight	Part no.	ϕA	ϕB	ϕC	ϕD	Weight		
S-ZP04BA □	4	4.5	1.8	1.8	2.2	0.3	S-ZP10BA □	10	11	2	6	0.8		
S-ZP06BA □	6	7	2	3.4	3		S-ZP13BA □	13	14	3	8.4	1.0		
S-ZP08BA □	8	9		5.2		0.4	S-ZP16BA □	16	17		11.4	1.1		

Adapter

Adapter with one-touch fitting with Male thread A5, A6							Adapter with one-touch fitting with Female thread B4, B5, B6						Barb fitting U2, N4, U4, N6, U6 <small>N: Nylon tube U: PU tube</small>												
a1							a2						a3												
Part no.	A	B	ϕC	D	E	L	Weight	Part no.	A	B	ϕC	D	Weight	Part no.	A	ϕB	ϕC	E	H	Q	Weight				
ZPRS-04-A5	M5x0.8	20.6	4	4	7	46	17.8	ZPRS-04-B4	M4x0.7	20.6	4	4	12.2	M-3AU2	M3x0.5	4	0.9	2.5	4.5	6.5	0.7				
ZPRS-06-A5	M5x0.8	21.6	6	4	7	18.3	ZPRS-06-B4	M4x0.7	21.6	6	4	12.7	M-5AU2	M5x0.8	3	7	1.5	M-3AU4	M3x0.5	3.4	1.2	2.5	6	7.5	0.7
ZPRS-04-A6	M6x1.0	20.6	4	3	8	18.5	ZPRS-04-B5	M5x0.8	20.6	4	5	11.6	M-5AN4	M5x0.8	2.8	1.8	3	7	5	1.6					
ZPRS-06-A6	M6x1.0	21.6	6	6	12	ZPRS-06-B5	M6x1.0	21.6	6	6	12.5	M-5AU4	M5x0.8	3.4	1.8	5					1.6				
							ZPRS-04-B6	M6x1.0	20.6	4	6	11	M-5AN6	M5x0.8	4.5	2.5					7	1.7			
							ZPRS-06-B6	M6x1.0	21.6	6	6	12	M-5AU6	M5x0.8	4.95	2.5	7	1.8							
B5, 04, 06							03, 23, 04, 06						Hex. socket head male connector 03S, 23S, 04S, 06S												
a4							a5						a6												
Part no.	ϕD	L	Weight	ϕD	Part no.	A	ϕB	E	H	Q	Weight	ϕD	Part no.	A	ϕB	ϕC	E	H	Q	Weight					
ZPEA-B5-A12	-	20.5	15	3	KJH03-M3-B	M3x0.5	1.5	2.5	7	13.7	2.2	3	KJS03-M3-B	M3x0.5	1.5	7	2.5	1.5	13.7	1.4					
ZPEA-04-A12	4	23.5	17	3.2	KJH03-M5-B	M5x0.8	2.5	3			2	3	2	16.6	2		KJS03-M5-B	M5x0.8	2	3	2	16.6	2		
ZPEA-06-A12	6	23.7	15	4	KJH23-M3-B	M3x0.5	1.5	2.5	8	13.7	1.8	3	KJS23-M3-B	M3x0.5	1.5	8	2.5	1.5	13.7	1.4					
				4	KJH23-M5-B	M5x0.8	2.5	3			1.6	3	2	16.6	2.2		KJS23-M5-B	M5x0.8	2	3	2	16.6	2.2		
				6	KJH04-M3-B	M3x0.5	1.5	2.5	10	14.7	2	3	KJS04-M3-B	M3x0.5	1.5	10	2.5	1.5	13.7	1.6					
				6	KJH04-M5-B	M5x0.8	2.5	3			2.4	3	2.5	15.6	2.6		KJS04-M5-B	M5x0.8	2.5	3	2.5	15.6	2.6		
					KJH06-M5-B	M5x0.8	2.5	3	3.4	6	KJS06-M5-B	M5x0.8	2.5	6	KJS06-M5-B	M5x0.8	2.5	6	16.4	3.2					